

USN

10CV65

Sixth Semester B.E. Degree Examination, June/July 2016 Hydraulic Structures and Irrigation Design - Drawing

Time: 4 hrs.

Max. Marks:100

Note: 1. Answer any TWO full questions, from Part – A and any ONE question from Part – B.

2. Assume missing data suitably.

PART - A

- a. Explain the graphical method for the determination of the required storage capacity of a reservoir when the demand is i) Uniform ii) Non-uniform. (07 Marks)
 - b. Write short notes on any two of the following:

 i) Flood control reservoir

 ii) Distribution reservoir

 iii) Multipurpose reservoir.
 - i) Flood control reservoir
 ii) Distribution reservoir
 iii) Multipurpose reservoir.
 c. The construction costs for certain possible heights of a dam at a given site have been estimated and the storage capacity for all these dam heights are tabulated in the table below:

Sl.No	Height of the dam	Construction cost	Storage in million
	in meter	in million rupees	cubic meters
1	10	04	50
2	20	. 08	100
3	30	12	180
4	40	18	250
5	50	27	350
6	60	39	500
7	64	50	600

Determine the most economical height of the dam.

(04 Marks)

(09 Marks)

- 2 a. Define Gravity dam. Explain with neat sketch the drainage galleries in gravity dam.
 (06 Marks)
 - b. Following data were obtained from the stability analysis of a concrete gravity dam:
 - i) Total overturning moment about toe = 1.1×10^6 kN-m.
 - ii) Total resisting moment about toe = 2.1×10^6 kN-m.
 - iii) Total vertical force about base = 54,000 kN.
 - iii) Total vertical force about base 54,000
 - iv) Base width of the dam = 50m.
 - v) Slope of the D/S face = 0.8H:1V.

Calculate the maximum and minimum vertical stress to which the foundation will be subjected to, what is the maximum principal stress at toe? Assume there is no tail water.

- a. Explain the two different methods which are adopted for constructing earthen dams. Which of these methods would you prefer and why? (06 Marks)
 - b. What precautions and remedial measures would you undertake to control the seepage through, i) Earthen dam body ii) The dam foundation. (09 Marks)



Design a surplus weir for the following data: Combined catchment area = 51km²; Intercepted catchment area = 46km²; Top bund level (TBL) = 100.00m; Maximum water level (MWL) = 98.50 m; Full tank level (FTL) = 97.5m; Average ground level at proposed site = 96.5m; Top width of tank bund = 2m; Side slopes of bund on either side = 2:1; Level of hard strata for foundation = 95.00m; The ground level below the weir (D/S of weir) slopes to a level of 95.50m in a distance of about 6m.

Ryve's co-efficient C = 8; Modified Ryve's coefficient C = 2.5.

Provisions may be made to make Kutcha regulating arrangements to store water upto MWL in terms of necessity.

(25 Marks)

Draw to a suitable scale the following views of the above designed surplus weir.

- a. Cross section of weir.
- b. Draw half longitudinal section and half longitudinal elevation.
- c. Draw half plan at foundation and half plan at ground level.

(15 Marks) (20 Marks)

(10 Marks)

5 Design a canal regulator –cum – road bridge with the following particulars: Hydraulic particulars of canal upstream: Full supply discharge = 20m³/sec;

Bed width = 15m; Bed level = 20.0m; Full supply depth = 2.0m;

Full supply level = +22.0m; Top level of bank = +23.0m.

The right bank is 5m wide and left bank is 2m wide.

Hydraulic particulars of canal downstream: Full supply discharge = 16m³/sec:

Bed width = 15m; Bed level = +20.0m; Full supply depth = 1.75m;

Full supply level = +21.75m; Top level of bank = +22.75m. (25 Marks)

Top width of banks are the same as those on the upstream side. The regulator carries a road way single lane designed for I.R.C loading class 'A'. Provide clear freeboard of one meter above F.S.L for road bridge. Good foundation soil is available at +19.00. Assume the ground level site as +22.00. The co-efficient of drawing ratio for 80% is 1.645, 85% is 1.58 and 90% is 1.358.

Draw:

a. Cross section showing half elevation and half section.

(10 Marks)

b. Longitudinal section.

(15 Marks)

c. Half plan at foundation and half pan at ground level.

(20 Marks)
