

USN

--	--	--	--	--	--	--	--	--	--



10CS63

**Sixth Semester B.E. Degree Examination, June/July 2017**  
**Compiler Design**

Time: 3 hrs.

Max. Marks:100

**Note: Answer FIVE full questions, selecting  
at least TWO questions from each part.**

**PART - A**

- 1
  - a. List the phases of compiler in order. Use these phases to translate  $a = bc * cd + 50.00$  into the target code in assembly language. (08 Marks)
  - b. What are the applications of compiler? Explain. (08 Marks)
  - c. Write the regular definition and transition diagram for valid unsigned number. (04 Marks)
  
- 2
  - a. Why it is necessary for regular expression to define the lexical syntax of a languages? Give reasons. (04 Marks)
  - b. Define ambiguity. Is the following grammar ambiguous? If yes remove the ambiguity and rewrite the grammar  

$$\langle \text{stmt} \rangle \rightarrow \text{if} \langle \text{expr} \rangle \text{ then} \langle \text{stmt} \rangle$$

$$\quad \quad \quad | \text{if} \langle \text{expr} \rangle \text{ then} \langle \text{stmt} \rangle \text{ else} \langle \text{stmt} \rangle$$

$$\quad \quad \quad | a$$

$$\langle \text{expr} \rangle \rightarrow b$$
  - c. Find the FIRST and FOLLOW set for the following grammar (08 Marks) (05 Marks)
 
$$E \rightarrow TX$$

$$T \rightarrow (E) / \text{int } Y$$

$$X \rightarrow +E / \epsilon$$

$$Y \rightarrow *T / \epsilon$$
 Fig. Q2 (c)
  - d. When we say that the grammar G is LL(1) grammar? (03 Marks)
  
- 3
  - a. Write an algorithm to construct predictive parser table. Construct a predictive parser table for grammar given in Fig. Q2 (c), and parse the string  $w = \text{int}$ . (12 Marks)
  - b. Define handle, handle pruning with example. (03 Marks)
  - c. What are the actions a shift-reduce parser makes? Write the parse tree and shift-reduce configurations for the derivation  $S \xRightarrow{*} \alpha B x A z \Rightarrow \alpha B x y z \Rightarrow \alpha x y z$ . (05 Marks)
  
- 4
  - a. Write a schematic of LR parser. Write the canonical collection of set of LR(0) items and SLR parsing table for the following grammar: (14 Marks)
 
$$E \rightarrow E + T / T$$

$$T \rightarrow T * F / F$$

$$F \rightarrow (E) / \text{id}$$
  - b. Construct LR(1) goto graph for below grammar: (06 Marks)
 
$$X \rightarrow YZ / a$$

$$Y \rightarrow bZ / \epsilon$$

$$Z \rightarrow \epsilon$$

Important Note : 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.  
2. Any revealing of identification, appeal to evaluator and /or equations written eg,  $42+8 = 50$ , will be treated as malpractice.



**PART - B**

- 5 a. Define synthesized attribute, inherited attributes and attribute grammar. (03 Marks)
- b. Write a SDD and annotated parse tree for  $u^*s$  for below grammar suitable for top-down parser. (07 Marks)
- $T \rightarrow T * F / F$   
 $F \rightarrow \text{digits}$
- c. Construct a syntax tree for expression  $a+b-c$  using the grammar (06 Marks)
- $E \rightarrow E + T / E - T / T$   
 $T \rightarrow (E) / \text{id} / \text{num}$
- d. What is the need for eliminating left-recursion? Eliminate left recursion from SDT (04 Marks)
- $E \rightarrow E + T \{\text{print}('+')\}$   
 $E \rightarrow T$
- 6 a. Which are the common three address instruction forms? Explain. (09 Marks)
- b. Define jumping code. Translate the following code to jumping code: (05 Marks)
- if ( $X < 10 \parallel X > 20 \&\& X = Y$ )  $X = 1$
- c. Translate the following switch statement to intermediate code. (06 Marks)
- ```
Switch (E) {  
    Case  $V_1$  :  $S_1$  break ;  
    Case  $V_2$  :  $S_2$  break ;  
    .  
    .  
    .  
    Case  $V_{n-1}$  :  $S_{n-1}$  break ;  
    Default :  $S_n$   
}
```
- 7 a. Write the possible activations and activation tree corresponding to quick sort call quicksort (1, 9). (06 Marks)
- b. What are the basic functions and properties of memory management? Explain locality in program in detail. (08 Marks)
- c. What is garbage collection? What are the performance metric that must be considered when designing a garbage collector? (06 Marks)
- 8 a. Write intermediate code and flow graph for below code (10 Marks)
- ```
for i from 1 to 10 do  
    for J from 1 to 10 do  
        a[i, J] = 0.0  
    for i from 1 to 10 do  
        a[i, i] = 1.0
```
- b. What is the need for optimization? List and explain any three local optimization methods. (10 Marks)

\*\*\*\*\*