



USN

--	--	--	--	--	--	--	--	--	--

10EC64

Sixth Semester B.E. Degree Examination, June/July 2019
Antennas and Propagation

Time: 3 hrs.

Max. Marks: 100

Note: Answer any FIVE full questions, selecting atleast TWO questions from each part

PART - A

- 1 a. Define the following terms :
i) Beam area ii) Effective height iii) Directivity iv) Radiation pattern. (12 Marks)
b. What is Friis formula? How can it be used for the calculation of power at a receiving point. (05 Marks)
c. A radio link has 150W transmitter connected to an antenna of 2m^2 aperture at 2GHz. The receiving antenna has a aperture of 1.5m^2 and is located at 10km. Find the power delivered to the receiver. (03 Marks)
- 2 a. Define a point source. State the power theorem as applied to a point source. (06 Marks)
b. Calculate the directivity of a broad side array of two identical isotropic sources feed with currents of same magnitude and phase spaced $\lambda/4$ apart along the polar axis. The relative field pattern is give by $E = \text{Cos}(\pi/2 \cos \theta)$ where θ is the polar angle. (06 Marks)
c. Obtain the expression for the field due to a broad side array of n elements. (08 Marks)
- 3 a. Derive the radiation resistances in the case of
i) Thin linear dipole ii) $\lambda/2$ dipole. (10 Marks)
b. Given for an antenna $R_r = 73\Omega$, $R_L = 7\Omega$ and $G = 10\text{dB}$. Compute its efficiency and directivity. (06 Marks)
c. Write short note on V antennas. (04 Marks)
- 4 a. Derive the expression for the field strengths E_ϕ and H_θ in the case of a small loop. (10 Marks)
b. Explain the slot and complementary antennas. (06 Marks)
c. Explain microstrip antennas with neat sketches and mention its advantages. (04 Marks)

PART - B

- 5 a. Explain the practical design and operation for the monofilar axial mode helical antenna. (07 Marks)
b. Explain the working of log periodic antenna. (07 Marks)
c. Explain the theory behind Yagi – Uda array. (06 Marks)
- 6 a. Write short notes on :
i) Antennas for ground penetrating radar.
ii) Ultra – wide band antennas. (14 Marks)
b. Explain Turnstile antenna. (06 Marks)
- 7 a. Discuss the different forms of radio wave propagations. (08 Marks)
b. Derive an expression for space wave field intensity. (08 Marks)
c. A TV transmitter (T) uses an antenna of height 200m. The height of receiving antenna (R) for this transmitter is 20m. Obtain the maximum spacing between T and R through tropospheric propagation. Compute also the radio horizon in this case. (04 Marks)

Important Note : 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.
2. Any revealing of identification, appeal to evaluator and /or equations written eg, 42+8 = 50, will be treated as malpractice.



10EC64

- 8 a. For Ionospheric layer, derive the expression for conductivity and relative permittivity as a function of electron density and angular frequency. (08 Marks)
- b. Calculate the value of the operating frequency of the ionospheric layer specified by a refractive index 0.85 and an electron density of 5×10^5 electrons/cm³. (04 Marks)
- c. Calculate the value of the skip distance given that the height of the ionospheric layer is 50km, MUF is 29MHz and its critical frequency is 4MHz. (04 Marks)
- d. Write short note on Diffraction. (04 Marks)
