

ngineerin

(10 Marks)

- Develop Radix -2 DIF FFT algorithm and draw complete signal flow graph for N = 8. 6 a.
 - b. Compute the 8- point IDFT of a sequence. $X(k) = \{7, -0.707 - j0.707, -j, 0.707 - j0.707, 1, 0.707 + j0.707, j, -0.707 + j0.707\} using$ Radix – 2 DIF FFT algorithm. (10 Marks)

Module-4

Derive an expression for the order of analog Butterworth prototype low pass filter. (08 Marks) 7 а b. Design a digital Butterworth filter using Bilinear transformation method to meet following : Stopband attenuation ≤ 1.25 dB at passband edge frequency of 200Hz and i) – ii) Stopband attenuation \geq 15dB at stopband edge frequency of 400Hz. Take sampling frequency of 2KHz. (12 Marks)

An analog third order Butterworth low-pass filter has the transfer function 8 a.

 $H_9(s) = \frac{1}{(s+1)(s^2+s+1)}$. Design the corresponding digital filter using impulse invariance (08 Marks)

method.

b. Obtain direct form – I, direct form – II, Cascade form and Parallel form realization of the system defined by

$$H(z) = \frac{(z-1)(z-3)(z^2+5z+6)}{(z^2+6z+5)(z^2-6z+8)}.$$

Module-

9 Design a linear – phase high pass FIR filter using Hamming window for the following а desired frequency response.

$$H_{d}(e^{jw}) = \begin{cases} 0 & ; & |w| < \frac{\pi}{4} \\ e^{-j^{2w}} & ; & \frac{\pi}{4} \le |w| \le \pi \end{cases}$$
 (08 Marks)

b. An FIR filter is defined by difference equation ;

 $y(n) = 2.x(n) + \frac{4}{5}x(n-1) + \frac{3}{2}x(n-2) + \frac{2}{3}x(n-3)$. Find lattice coefficients. Also draw direct form and lattice form.

c. Compare FIR filter with IIR filter.

(08 Marks) (04 Marks)

(12 Marks)

OR

Design a linear phase FIR filter using rectangular window for the following desired 10 a. frequency response

$$H_{d}(e^{jw}) = \begin{cases} e^{-j^{2}w} & ; & |w| < \pi/4 \\ 0 & ; & \pi/4 \le |w| \le \pi \end{cases}$$
 (08 Marks)

- b. Realize the FIR filter whose transfer function is given by $H(z) = 1 + \frac{3}{4}Z^{-1} + \frac{17}{8}Z^{-2} + \frac{3}{4}Z^{-3} + Z^{-4}$. Using Direct form I and Linear phase form. (08 Marks)
- c. Explain Gibbs phenomenon. Also mention methods to minimize it. (04 Marks)

* * * * * 2 of 2